




# Using FON-350i/360i Telephones with FortiVoice Enterprise Systems



The reference card includes the basic features.  
For more information, see the phone's user guide.

## Buttons

Most of the buttons are similar to those on other phones, but you might not be familiar with the following:

-  — Puts a call on hold.
-  — Toggles do not disturb on or off
-  — Opens configuration options or transfers a call

**Softkeys** — The screen shows the current function of each of the 3 softkeys. Softkeys change based on the call status.

## Remember

Press **#** or *Dial* after dialing an outside number or extension.

## Setting up voicemail

1. Press *Vmail*.
2. When prompted, enter a password, record a greeting and record your name for the dial-by-name directory.

## Checking voicemail

1. Press *Vmail*.
2. When prompted, enter your password + **#**.
3. Press **1** to listen to your messages. You can also change your greeting and personal options.


## Calling an outside number

1. Dial the phone number + **#** or press *Dial*.
2. If prompted, dial an access code.


## Calling an extension

Dial the extension number + **#** or press *Dial*. You can also press an extension appearance key if programmed to monitor a specific extension.

## Placing a caller on hold


Press  or *Hold*. You can now hang up or answer another call without disconnecting the caller.

## Retrieving a caller on hold


Press  or *Resume*. You can also press the flashing extension or line appearance key if it's associated with the call on hold.

## Performing a screened transfer

A screened transfer allows the recipient to accept or refuse the transfer.

1. Press  + <extension> (or outside number) + **#**.
2. When the recipient answers:
  - press *Transfer* or hang up to complete the transfer or
  - press *EndCall*, then *Resume* to retrieve the caller on hold and cancel the transfer.

## Performing a blind transfer

Press  + <extension> (or outside number) + *Dial*, and hang up.

## Key states

Light	Status
Flashing green (rapid)	Incoming call
Solid green	This extension is in use
Flashing green (slow)	Call on hold at this extension
Solid red	Line/extension/queue in use
Flashing red (slow)	Line/extension/queue on hold
Alternating red and yellow	Extension/line not registered
Solid yellow	Do No Disturb (DND) enabled

## Voicemail

### Access mailbox:

Locally *Vmail*  
Remotely \* 9 8 #

Go to old messages 2

Change personal options 0  
(greetings, password, remote notification options)

### MESSAGE PLAYBACK CONTROLS

Go to first message 1

Restart 2

Go to end 3

Play previous message 4

Play next message 6

Delete message 7

Forward message 8

Save message 9

Exit #

**FORTINET**

## Using FON-350i/360i Phones with FortiVoice Enterprise Systems


### Accessing Features


**Do not disturb** Press  to toggle on/off.

**Pick up: Any ringing extension**  
Press *Pickup* (if programmed),  
or \* 8 0 + #.

**Pick up: Specific extension**  
Press the key associated with the extension,  
or \* 8 1 + <extension> + #.

**Place caller on hold** 

**Retrieve caller on hold**   
or the flashing key associated  
with the call on hold.



 CUT ↑ and FOLD →

## Accessing Features



### Answer call waiting

*Answer* or the flashing line appearance key.

### Screened transfer

 /  + <extension> (or outside number) + **#** + *Transfer*, or hang up.  
To cancel transfer, *EndCall* + *Resume* to connect to the caller on hold.

### Blind transfer

 /  + <extension> (or outside number) + *Dial*, and hang up.



### Voicemail transfer

 /  + **\*X** + <extension> + *Dial*, and hang up.

### Conference call

*More* + *Conf.* to put the first party on hold.  
Call the second party (for external calls, first access an outside line). Press *Join*.

### Park a caller

Press the programmed *Park* or  /  + **\*X 4** + **#**.  
The system will respond with a parking orbit.

### Two-way intercom paging to FortiFone telephones

Press the programmed *Intercom* + <extension> + *Dial*,  
or **\*X 9 2** + <extension> + **#**.

### Two-way group paging to FortiFone telephones

Dial the <paging group number> + **#**.