

Using FON-370i Telephones with FortiVoice Enterprise Systems



The reference card includes the basic features. For more information, see the phone's user guide.

Buttons

Most of the buttons are similar to those on other phones, but you might not be familiar with the following:

-  — Hold
-  — Toggles do not disturb on or off
-  — Transfer
-  — Settings
-  — Voicemail
-  — Redial

Softkeys — The screen shows the current function of each of the 4 softkeys. Softkeys change based on the call status.

Remember

Press **#** or *Send* after dialing an outside number or extension.

Setting up voicemail

1. Press *Voicemail* or .
2. When prompted, enter a password, record a greeting and record your name for the dial-by-name directory.

Checking voicemail

1. Press *Voicemail* or .
2. When prompted, enter your password + **#**.
3. Press **1** to listen to your messages. You can also change your greeting and personal options.

Calling an outside number

1. Dial the phone number + **#** or press *Send*.
2. If prompted, dial a PIN code.

Calling an extension

Dial the extension number + **#** or press *Send*. You can also press an extension appearance key if programmed to monitor a specific extension.

Placing a caller on hold

Press  or *Hold*. You can now hang up or answer another call without disconnecting the caller.

Retrieving a caller on hold

Press  or *Resume*. You can also press the flashing extension or line appearance key if it's associated with the call on hold.

Performing a screened transfer

A screened transfer allows the recipient to accept or refuse the transfer.

1. Press  + <extension> (or outside number) + **#**.
2. When the recipient answers:
 - press *Transfer* or hang up to complete the transfer or
 - press *End Call*, then *Resume* to retrieve the caller on hold and cancel the transfer.

Performing a blind transfer

Press  + <extension> (or outside number) + *Transfer*, and hang up.

Key states

Light	Status
Solid red	Line/extension/queue in use
Flashing green (slow)	Line/extension/queue on hold
Flashing red (slow)	Do No Disturb (DND) enabled
Flashing green (fast)	Line/extension is ringing

Voicemail

Access mailbox:

Locally

Voicemail or 

Remotely

* 9 8 #

Go to old messages

2

Change personal options

0

(greetings, password, remote notification options)

MESSAGE PLAYBACK CONTROLS

Go to first message

1

Restart

2

Go to end

3

Play previous message

4

Play next message

6

Delete message

7

Forward message

8

Save message

9

Exit

#

FORTINET

Using FON-370i Phones with FortiVoice Enterprise Systems

Accessing Features

Do not disturb Press  to toggle on/off.

Pick up: Any ringing extension

Press *Pickup* (if programmed),
or * 8 0 + #.

Pick up: Specific extension

Press the key associated with the extension,
or * 8 1 + <extension> + #.

Place caller on hold



Retrieve caller on hold



or the flashing key associated
with the call on hold.

 CUT ↑ and FOLD →

Accessing Features

Answer call waiting

Answer or the flashing line appearance key.

Screened transfer

[Left Arrow] + <extension> (or outside number) + **#** + *Transfer*, or hang up.
To cancel transfer, *End Call* + *Resume* to connect to the caller on hold.

Blind transfer

[Left Arrow] + <extension> (or outside number) + *Transfer*, and hang up.

Voicemail transfer

[Left Arrow] + ***x** + <extension> + *Send*, and hang up.

Conference call

Press *Conf* to put the first party on hold.
Call the second party (for external calls, first access an outside line). Press *Conf*.

Park a caller

Press the programmed *Park* or **[Left Arrow]** + ***x 4** + **#**.
The system will respond with a parking orbit.

Two-way intercom paging to FortiFone telephones

Press the programmed *Intercom* + <extension> + *Send*,
or ***x 9 2** + <extension> + **#**.

Two-way group paging to FortiFone telephones

Dial the <paging group number> + **#**.